

Registration No :

--	--	--	--	--	--	--	--	--	--

Total Number of Pages : 02

B.Tech/
Integrated Dual Degree (B.Tech and M.Tech)

RCS5C001

5th Semester Reg/Back Examination: 2024-25

Formal Languages and Automata Theory

CST, CSEDS, CSE, CSIT, CSEAIME, ELECTRICAL & C.E, ELECTRONICS &
C.E, IT, CSE

Time : 3 Hour

Max Marks : 100

Q. Code : R173

Answer Question No.1 (Part-1) which is compulsory, any eight from Part-II and any two from Part-III.

The figures in the right hand margin indicate marks.

Part-I

Q1 Answer the following questions: (2 x 10)

- Construct a CFG over $\{a,b\}$ generating a language consisting of equal number of a's and b's. Construct a CFG over $\{a,b\}$ generating a language consisting of equal number of a's and b's.
- Specify the use of context free grammar.
- Design a DFA over $\Sigma = \{a, b\}$ such that every string will be accepted must ends with 'aa' or 'bb'
- Is the language of Deterministic PDA and Non – deterministic PDA same?
- Classify different types of Turing Machine
- Define Arden's theorem
- Can a context-free grammar generate an infinite language?
- What do you mean by complement of DFA? Explain with suitable example
- Name any four closure properties of regular languages
- State the halting problem of Turing machine.

Part-II

Q2 Only Focused-Short Answer Type Questions- (Answer Any Eight out of Twelve) (6 x 8)

- What are the applications of Turing Machine?
- Compare and contrast the Moore machine and Mealy machine models of finite state machines. Provide five distinct points of comparison.
- Apply the identities of regular expressions to prove the following:
 $(1+00^*1)+(1+00^*1)(0+10^*1)^*(0+10^*1) = 0^*1(0+10^*1)^*$.
- Convert the following grammar into CNF $S \rightarrow cBA$, $S \rightarrow A$, $A \rightarrow cB$, $A \rightarrow AbbS$, $B \rightarrow aaa$

- e) Construct a minimum state automaton equivalent to given automaton whose transition table is given below:

States/Input	a	b
→q0	q1	q3
q1	q2	q4
q2	q1	q4
q3	q2	q4
*q4	q4	q4

- f) Are there any languages which are not recursively enumerable, but accepted by a multi-tape Turing machine? Justify your answer.
- g) Construct ϵ -NFA for the regular expression $R = (cd | c)^*$. Construct the equivalent DFA by ϵ -closure method for the given regular expression
- h) Consider the grammar G, where the productions are
 $E \rightarrow F - E | E - F | F$
 $F \rightarrow a | b$
 Prove that the Grammar is ambiguous for the string $a - b$
- i) Convert the following grammar into an equivalent one with no unit productions and no useless symbols $S \rightarrow ABA$ $A \rightarrow aAA|aBC|bB$ $B \rightarrow A|bB|Cb$ $C \rightarrow CC|Cc$
- j) Does a Push down Automata have memory? Justify.
- k) List the main application of pumping Lemma in CFL's
- l) Are NPDA (Nondeterministic PDA) and DPDA (Deterministic PDA) equivalent? Illustrate with an example.

Part-III

Only Long Answer Type Questions (Answer Any Two out of Four)

- Q3 Explain the Chomsky hierarchy of languages, including the four types of languages and their associated grammars. (16)
- Q4 Let G be the grammar: $S \rightarrow 0B | 1A$, $A \rightarrow 0 | 0S | 1AA$, $B \rightarrow 1 | 1S | 0BB$. For the string 00110101 find: (a) The leftmost derivation (b) The rightmost derivation (c) The derivation tree (5+5+6)
- Q5 What is the purpose of normalization? Construct the CNF and GNF for the following grammar and explain the steps: $S \rightarrow aAa | bBb | \epsilon$ $A \rightarrow C|a$ $B \rightarrow C|b$ $C \rightarrow CDE | \epsilon$ $D \rightarrow A|B|ab$. Construct a CFG for the regular expression $(011+1)(01)$ (2+8+6)
- Q6 Discuss variants of Turing Machine. Design a Turing Machine that will accept the language $L = \{0^n 1^n | n \geq 1\}$. (4+12)